



COMPUTER SCIENCE STANDARD LEVEL PAPER 1

Tuesday 19 May 2009 (afternoon)

1 hour 30 minutes

INSTRUCTIONS TO CANDIDATES

- Do not open this examination paper until instructed to do so.
- Section A: answer all the questions.
- Section B: answer all the questions.

SECTION A

Answer **all** the questions.

1.	Explain two differences between the analysis and design stages of the softw development life cycle.	vare [4 marks]			
2.	Explain two advantages of using a modular approach in constructing comp programs.	uter [4 marks]			
3.	The implementation of computer systems often has an effect on individuals. Describe a situation where a new system could have				
	(a) a positive effect on a group of people.	[2 marks]			
	(b) a negative effect on a group of people.	[2 marks]			
4.	State two functions of an operating system.	[2 marks]			
5. The method calculateHours(), listed below, is called by the statement					
	<pre>double hours = calculateHours(minutes);</pre>				
	<pre>public void calculateHours(double mins)</pre>				
	<pre>double h = mins/60; }</pre>				
	An attempt is made to compile the program.				
	(a) Define the term <i>compilation</i> .	[2 marks]			
	(b) By considering the code given above, identify the type of error that would cathe compilation process to fail.	nuse [1 mark]			
	(c) Explain the reason why this error has occurred.	[2 marks]			
6.	Describe a single data structure that would store the following data:				
	(a) rainfall data on 30 consecutive days	[3 marks]			
	(b) the age of a person and whether or not football is his/her favourite sport	[3 marks]			

7.	Outline the function of the <i>address bus</i> .	[2 marks]
8.	Express the 8-bit binary number 01011111 in	
	(a) hexadecimal.	[1 mark]
	(b) decimal.	[1 mark]
9.	Outline what is meant by the term <i>user-defined method</i> in relation to Ja	va programs. [1 mark]

2209-7013 Turn over

SECTION B

Answer **all** the questions.

10. Consider the class SelectionSort shown below.

```
public class SelectionSort
  public static void main(String[] args)
     int[] unsortedArray = {3,6,2,8,5};
     int[] sortedArray = selection(unsortedArray);
  public static int[] selection(int[] list) // sorts array in ascending order
     for (int x = 0; x < 4; x++)
       int p = x;
       int smallest = list[p];
       for (int y = x + 1; y < 5; y++)
         if (list[y] < smallest)</pre>
           p = y;
           smallest = list[y];
                             // end of 'y' loop
       if (p != x)
         list[p] = list[x];
         list[x] = smallest;
                             // end of 'x' loop
    return list;
```

(a) Describe the information given in the following line.

- (b) State the values of the array list[] when the end of the 'x' loop is reached for the first time. [2 marks]
- (c) Explain what would happen if the array unsortedArray[] was already sorted. [2 marks]
- (d) Explain, without writing code, how the method selection () could be modified to sort an integer array of any size. [2 marks]

11.	Ever	ry month the payroll program is run during which the master file is updated by a saction file.			
	(a)	With reference to the payroll program, explain the relationship between the master file and the transaction file.	[4 marks]		
	(b)	Identify the characteristics of the above system that would allow batch processing to take place.	[2 marks]		
	(c)	Outline			
		(i) how a deliberate error could enter the system.	[2 marks]		
		(ii) how the company could try to prevent this type of error.	[2 marks]		
12.		ompany uses a <i>wide area network</i> (WAN) for a variety of reasons, one of which is sending of large files between one office and another.			
	(a)	Discuss two ways in which the company could speed up the transmission of these files.	[4 marks]		
	(b)	Explain the need for protocols in this network.	[2 marks]		
	(c)	Other than sending files, describe two examples where the company could use its WAN.	[4 marks]		
13.	Many modern devices use microprocessors.				
	(a)	Define the term <i>microprocessor</i> .	[2 marks]		
	(b)	Identify a device, other than a computer, that uses a microprocessor.	[1 mark]		
	(c)	For this device, describe			
		(i) the function of its microprocessor.	[2 marks]		
		(ii) its inputs.	[1 mark]		
		(iii) its outputs.	[1 mark]		
	(d)	Describe two different types of memory that might be found within the microprocessor from part (b).	[3 marks]		